

LION XV88N

Digital Signal Processor



Product Introduction

The digital signal processor equipped with a high-performance 32-bit floating-point DSP processor and A/D ~ D/A converter, support for 24bit/48KHz sampling frequency, high-quality 21-stage preamplifier circuit, DSP processing bus structure built-in feedback cancellation, echo cancellation, noise suppression, automatic mixing and other audio core algorithms, to restore high-quality sound, with a comprehensive matrix mixing function. It supports multiple scene presets, scene saving and other functions, and user-friendly control software interface. Mainly used in a variety of large places, can meet the theatre, concert halls, remote video conferencing, stadiums, churches, conference center, theme parks, public sound reinforcement systems and other aspects of the application needs.

Product Features

- Highly integrated, integrating a variety of traditional Analog audio processing equipment in a Digital audio processor;
- High-performance 32-bit floating-point DSP processor, all-digital processing, fast response to feedback cancellation, echo cancellation, noise suppression and other core algorithms;
- High-performance A/D, D/A converter, 24bit/48KHz sampling frequency, high-quality Analog

→ Digital, Digital → Analog conversion;

- 8 Analog input channels and 8 Analog output channels, very small distortion and ultra-low background noise;
- Rich interface expansion;
- Humanization, graphical, intuitive and easy-to-operate control software interface;
- Integrated design of audio processing, wireless microphone and amplifier outputs;
- Comprehensive matrix mixing functions;
- Scene storage is different from the Analog equipment is one of the most practical and significant features, can store 100 complete scenes, all the scenes can be exported to an external storage device for storage backup, so that the later call at any time.

Functions

- ✧ Comprehensive matrix mixing function, 48kHz sampling rate, 24-bit high performance A/D, D/A converter and 32-bit floating point DSP processor;
- ✧ DSP audio processing, built-in automatic mixing console, including mixing and automatic mixing functions, but also has a mixing component control function; at the same time with AFC, AEC, ANS module; AFC: Support notch feedback cancellation algorithm, manual and automatic notch feedback canceler, with manual, dynamic, fixed three modes, can automatically capture the feedback point or manually set the feedback point, the maximum support for the capture of 16 feedback points, the maximum depth of inhibition up to 24dB;
- ✧ Inputs per channel: Preamplifier 51dB, Invert, Signal Generator, Expander, Equalizer (5/8/12-band Parametric Equalizer, 10/15/31-band Graphic Equalizer), Compressor, Automatic Gain Control (AGC), AM (Gain Sharing Automatic Mixer or Gating Automatic Mixer), Ducker, Acoustic Feedback Canceler (AFC), Acoustic Echo Canceler (AEC), Adaptive Noise Suppressor (ANS), Parametric Equalizer filter type selectable (Low Shelf, High Shelf, Low Pass Filter, High Pass Filter);
- ✧ Outputs per channel: Delay, Crossover, Equalizer (5/8/12-band Parametric Equalizer, 10/15/31-band Graphic Equalizer), Limiter, Invert, Parametric Equalizer filter type selectable (Low Shelf, High Shelf, Low Pass Filter, High Pass Filter);
- ✧ Integrated design of audio processor, wireless microphone input and amplifier output;
- ✧ Display shows radio frequency and channel information;
- ✧ Test signal generator, Sine wave, Pink Noise, White Noise, frequency and level magnitude

selectable;

- ✧ Input phase button, mute button, phantom power button;
- ✧ Output mute button, phase button per channel;
- ✧ Supports Simplified Chinese, English and Traditional Chinese languages;
- ✧ One-click display of all function modules;
- ✧ Storing user manual and software with the device;
- ✧ Central control code generated in the control software; power failure automatic protection memory function; one-click reset function;
- ✧ Channel copy, paste, group control function;
- ✧ Supports setting the maximum and minimum volume range for each channel;
- ✧ The same host allows 10 users to manage;
- ✧ Device name can be modified;
- ✧ Editable preset mode, new, delete, modify, one-click reset, preset mode can be stored to computer and one-click reset;
- ✧ With camera tracking function, can independently adjust the preset position of a camera, compatible with VISCA, PELCO-D, PELCO-P three control protocols, support for custom commands;
- ✧ Convenient and fast web control: Built-in web controller for fast operation on Windows, macOS, Linux, Android, iOS and other OS platforms;
- ✧ Ethernet multi-purpose data transmission and control port, can support real-time management of single and multiple devices;
- ✧ Intuitive image, simple and easy to understand the graphical software control interface, for customers to bring fast, real-time operating experience;
- ✧ The device does not need a CD, comes with installation software, a device for a software version, to solve the troubles caused by the loss of the installation CD and the confusion of multiple software versions;
- ✧ Extendable USB interface, support U disk recording and playback, or USB sound card, please refer to the actual device;
- ✧ Configuration of bi-directional RS232 interface, RS485 interface, standard Ethernet control interface, 8-channel programmable GPIO control interface (customisable inputs and

outputs), level support for external inputs 3.3 ~ 24V;

- ✧ Support 100 groups of scene presets, scene new, save, delete and other functions;
- ✧ Intuitive, graphical software control interface, works on Windows XP, 7, 8, 10, 11, etc.;
- ✧ Support mobile iOS, iPadOS, Android control software.

Specification

Category	Parameter Item	Parameter Description
Peripherals	Input Interfaces	8 Analog
	Output Interfaces	8 Analog
	Display	Displays radio frequency and channel information
	UHF wireless microphone Channels	2
	Digital Amplifier Channels	2x150W
	Control Interfaces	1 RJ45 interface, 1 RS232 interface
Audio processing	Processor	TI 456MHz FLOPS dual-core 32-bit DSP processor; 24-bit A/D and D/A converter, 48kHz sampling rate
	Input Channel	Functional module: Preamplifier 51dB, Signal Generator, Expander, Equalizer (5/8/12-band Parametric Equalizer, 10/15/31-band Graphic Equalizer), Compressor, Automatic Gain Control (AGC), AM (Gain Sharing Automatic Mixer or Gating Automatic Mixer), Ducker, Acoustic Feedback Canceler (AFC), Acoustic Echo Canceler (AEC), Adaptive Noise Suppressor (ANS), Parametric Equalizer filter type selectable (Low Shelf, High Shelf, Low Pass Filter, High Pass Filter). Physical interface: Balanced Phoenix terminals
	Output Channel	Functional module: Delay, Crossover, Equalizer (5/8/12-band Parametric

		Equalizer, 10/15/31-band Graphic Equalizer), Limiter, Parametric Equalizer filter type selectable (Low Shelf, High Shelf, Low Pass Filter, High Pass Filter). Physical interface: Balanced Phoenix terminals
	Phantom Power	DC 48V
	Input Impedance	Balanced: 20K Ω
	Output Impedance	Balanced: 100 Ω
	Common Mode Rejection Ratio	>60dB@50Hz
	Input Dynamic Range	108dB
	Frequency Response	20Hz~20KHz, ± 0.2 dB
	Noise Floor	-90dBu
	Signal-to-Noise Ratio	106dB
	THD+N	$\leq 0.003\%$ @1kHz, +4dBu
	Channel Isolation	>100dB@1kHz
	Input Range	$\leq +18$ dBu (A-Weighting)
	Crossover	Three types of high and low pass filters: Butterworth, Bessel and Linkwitz-Riley
	Equalizer	- Parametric Equalizer: Frequency: 20 to 20kHz, Gain: -15 to +15dB, Bandwidth: 0.02 to 4 - Graphic Equalizer: Frequency: 20~20kHz, Gain: -15~+15dB
	System Latency	≤ 9 ms
	Maximum Output Level	18dBu
	Maximum Input Level	18dBu

	Analog/Digital Dynamic Range	114dB
	Digital/Analog Dynamic Range	120dB
	Equivalent Input Noise	$\leq -125\text{dBu}$
General specification	Operating Voltage	AC 100V \sim 240V, 50Hz/60Hz
	Maximum Power	330W
	Operating Temperature and Humidity	0 $^{\circ}\text{C}$ \sim 40 $^{\circ}\text{C}$, 10% \sim 90%RH, No condensation
	Chassis	1U
	Product Dimensions (L \times W \times H)	482.4mm \times 260.5mm \times 44mm
	Net Weight	3kg
	Package Dimensions (L \times W \times H)	590mm \times 430mm \times 110mm
	Package Weight	3.5kg